

This document provides additional assistance with wiring your Extron IP Link enabled product to your device. Different components may require a different wiring scheme than those listed below.

For complete operating instructions, refer to the user's manual for the specific Extron IP Link enabled product or the controlled device manufacturer supplied documentation.

Device Specifications:

Device Type: Switcher
Manufacturer: Intelix
Firmware Version: N/A
Model(s): DIGI-P123, DIGI-P122

Minimum Software and Firmware Requirements:

IP Link Compiler	IP Link Firmware	GC Version
1.6.0	1.17	3.5.1

Version History:

Driver Version	Date	Notes
3	10/22/2013	Added DIGI-P122 model.
2	9/27/2013	Fixed range for Mic Volume.
1	9/6/2013	Initial version.

Driver Notes:

- Driver has been optimized for Volume.

Control Commands & States:

Auto Image	Execute		
Executive Mode	On	Off	
Freeze	On	Off	
Input	HDMI1	HDMI2	HDMI3
	HDMI4	VGA 1	VGA 2
	VGA 3	VGA 4	AV1
	AV2	YPbPr	S-Video
Line Mute	On	Off	
Line Volume (Discrete)	0 to 100 in steps of 1		
Line Volume (Step)	Up	Down	
Menu Navigation	Up	Down	Left
	Right	Menu	Enter
Mic Mute	On	Off	
Mic Volume (Discrete)	0 to 60 in steps of 1		
Mic Volume (Step)	Up	Down	
Mute All	On	Off	
Output Resolution	1360x768	1024x768	1280x720
	1280x800	1920x1080	

Status Available:

Connection Status	Connected	Disconnected	
Input	HDMI1 HDMI4 VGA 3 AV2	HDMI2 VGA 1 VGA 4 YPbPr	HDMI3 VGA 2 AV1 S-Video
Line Volume (Discrete)	0 to 100 in steps of 1		
Mic Volume (Discrete)	0 to 60 in steps of 1		
Output Resolution	1360x768 1280x800	1024x768 1920x1080	1280x720

Network communication:

When configuring the Ethernet driver, be sure device settings match that of the GC configuration.

Port Type:	Ethernet
Logon Credentials Supported:	No
Default Port:	4001
Multi-Connection Capable:	No
Port Changeable:	Yes

Ethernet Driver Configuration Description:

Please refer to user manual for settings and changes to the network communication parameters such as Port Number.

Notes for the Device: